

ADC10 Cheat Sheet
ADC10CTL0 ADC10 Control Register 0

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
SREFx			ADC10SHTx		ADC10SR	REFOUT	REFBURST	MSC	REF2_5V	REFON	ADC10ON	ADC10IE	ADC10IFG	ENC	ADC10SC

15	14	13	12	11	10	9	8
SREFx			ADC10SHTx		ADC10SR	REFOUT	REFBURST
7	6	5	4	3	2	1	0
MSC	REF2_5V	REFON	ADC10ON	ADC10IE	ADC10IFG	ENC	ADC10SC
7	6	5	4	3	2	1	0

Can be modified only when ENC = 0

SREFx	Bits 15-13	Select reference. 000 $V_{R+} = V_{CC}$ and $V_{R-} = V_{SS}$ 001 $V_{R+} = V_{REF+}$ and $V_{R-} = V_{SS}$ 010 $V_{R+} = V_{REF+}$ and $V_{R-} = V_{SS}$. Devices with V_{REF+} only. 011 $V_{R+} =$ Buffered V_{REF+} and $V_{R-} = V_{SS}$. Devices with V_{REF+} pin only. 100 $V_{R+} = V_{CC}$ and $V_{R-} = V_{REF-} / V_{REF-}$. Devices with V_{REF-} pin only. 101 $V_{R+} = V_{REF+}$ and $V_{R-} = V_{REF-} / V_{REF-}$. Devices with $V_{REF+/-}$ pins only. 110 $V_{R+} = V_{REF+}$ and $V_{R-} = V_{REF-} / V_{REF-}$. Devices with $V_{REF+/-}$ pins only. 111 $V_{R+} =$ Buffered V_{REF+} and $V_{R-} = V_{REF-} / V_{REF-}$. Devices with $V_{REF+/-}$ pins only.
ADC10SHTx	Bits 12-11	ADC10 sample-and-hold time 00 4 x ADC10CLKs 01 8 x ADC10CLKs 10 16 x ADC10CLKs 11 64 x ADC10CLKs
ADC10SR	Bit 10	ADC10 sampling rate. This bit selects the reference buffer drive capability for the maximum sampling rate. Setting ADC10SR reduces the current consumption of the reference buffer. 0 Reference buffer supports up to ~200 ksp/s 1 Reference buffer supports up to ~50 ksp/s
REFOUT	Bit 9	Reference output 0 Reference output off 1 Reference output on. Devices with V_{REF+} / V_{REF-} pin only.
REFBURST	Bit 8	Reference burst. 0 Reference buffer on continuously 1 Reference buffer on only during sample-and-conversion
MSC	Bit 7	Multiple sample and conversion. Valid only for sequence or repeated modes. 0 The sampling requires a rising edge of the SHI signal to trigger each sample-and-conversion. 1 The first rising edge of the SHI signal triggers the sampling timer, but further sample-and-conversions are performed automatically as soon as the prior conversion is completed
REF2_5V	Bit 6	Reference-generator voltage. REFON must also be set. 0 1.5 V 1 2.5 V
REFON	Bit 5	Reference generator on 0 Reference off 1 Reference on
ADC10ON	Bit 4	ADC10 on 0 ADC10 off 1 ADC10 on
ADC10IE	Bit 3	ADC10 interrupt enable 0 Interrupt disabled 1 Interrupt enabled
ADC10IFG	Bit 2	ADC10 interrupt flag. This bit is set if ADC10MEM is loaded with a conversion result. It is automatically reset when the interrupt request is accepted, or it may be reset by software. When using the DTC this flag is set when a block of transfers is completed. 0 No interrupt pending 1 Interrupt pending
ENC	Bit 1	Enable conversion 0 ADC10 disabled 1 ADC10 enabled
ADC10SC	Bit 0	Start conversion. Software-controlled sample-and-conversion start. ADC10SC and ENC may be set together with one instruction. ADC10SC is reset automatically. 0 No sample-and-conversion start 1 Start sample-and-conversion

ADC10CTL1 ADC10 Control Register 1

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
INCHx				SHSx		ADC10DF	ISSH	ADC10DIVx			ADC10SSELx		Convex		ADC10BUSY

15	14	13	12	11	10	9	8
INCHx				SHSx		ADC10DF	ISSH
rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)
7	6	5	4	3	2	1	0
ADC10DIVx		ADC10SSELx			CONSEQx		ADC10BUSY
rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	r-0

Can be modified only when ENC = 0

INCHx	Bits 15-12	Input channel select. These bits select the channel for a single-conversion or the highest channel for a sequence of conversions. Only available ADC channels should be selected. See device specific datasheet.
		0000 A0
		0001 A1
		0010 A2
		0011 A3
		0100 A4
		0101 A5
		0110 A6
		0111 A7
		1000 V_{REF+}
		1001 V_{REF-}/V_{REF+}
		1010 Temperature sensor
		1011 $(V_{CC} - V_{SS}) / 2$
		1100 $(V_{CC} - V_{SS}) / 2$, A12 on MSP430F22xx devices
		1101 $(V_{CC} - V_{SS}) / 2$, A13 on MSP430F22xx devices
		1110 $(V_{CC} - V_{SS}) / 2$, A14 on MSP430F22xx devices
		1111 $(V_{CC} - V_{SS}) / 2$, A15 on MSP430F22xx devices
SHSx	Bits 11-10	Sample-and-hold source select.
		00 ADC10SC bit
		01 Timer_A.OUT1 ⁽¹⁾
		10 Timer_A.OUT0 ⁽¹⁾
		11 Timer_A.OUT2 (Timer_A.OUT1 on MSP430F20x0, MSP430G2x31, and MSP430G2x30 devices) ⁽¹⁾
ADC10DF	Bit 9	ADC10 data format
		0 Straight binary
		1 2s complement
ISSH	Bit 8	Invert signal sample-and-hold
		0 The sample-input signal is not inverted.
		1 The sample-input signal is inverted.
ADC10DIVx	Bits 7-5	ADC10 clock divider
		000 /1
		001 /2
		010 /3
		011 /4
		100 /5
		101 /6
		110 /7
		111 /8
ADC10SSELx	Bits 4-3	ADC10 clock source select
		00 ADC10SC
		01 ACLK
		10 MCLK
		11 SMCLK
CONSEQx	Bits 2-1	Conversion sequence mode select
		00 Single-channel-single-conversion
		01 Sequence-of-channels
		10 Repeat-single-channel
		11 Repeat-sequence-of-channels
ADC10BUSY	Bit 0	ADC10 busy. This bit indicates an active sample or conversion operation
		0 No operation is active.
		1 A sequence, sample, or conversion is active.

ADC10AE0 Analog (Input) Enable Control Register 0

7	6	5	4	3	2	1	0
ADC10AE0x							

ADC10AE0x Bits 7-0 ADC10 analog enable. These bits enable the corresponding pin for analog input. BIT0 corresponds to A0, BIT1 corresponds to A1, etc. The analog enable bit of not implemented channels should not be programmed to 1.

0 Analog input disabled
1 Analog input enabled

ADC10AE1 Analog (Input) Enable Control Register 1

7	6	5	4	3	2	1	0
ADC10AE1x				Reserved			

ADC10AE1x Bits 7-4 ADC10 analog enable. These bits enable the corresponding pin for analog input. BIT4 corresponds to A12, BIT5 corresponds to A13, BIT6 corresponds to A14, and BIT7 corresponds to A15. The analog enable bit of not implemented channels should not be programmed to 1.

0 Analog input disabled
1 Analog input enabled

Reserved Bits 3-0 Reserved

ADC10MEM Conversion-Memory Register, Binary Format (Read Only Register)

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
0	0	0	0	0	0	Conversion Result									

This is the data format of ADC10MEM when Bit ADC10DF is 0

Conversion Result, Bits 15-0, The 10-bit conversion results are right justified, straight-binary format. Bit 9 is the MSB. Bits 15-10 are always 0.

ADC10MEM Conversion-Memory Register, 2s Complement Format (Read Only Register)

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Conversion Result										0	0	0	0	0	0

This is the data format of ADC10MEM when Bit ADC10DF is 1

Conversion Result Bits 15-0, The 10-bit conversion result is left-justified, 2s complement format. Bit 15 is the MSB. Bits 5-0 are always 0

ADC10DTC0 ADC10 Data Transfer Control Register 0

7	6	5	4	3	2	1	0
Reserved				ADC10TB	ADC10CT	ADC10B1	ADC10FETCH

7	6	5	4	3	2	1	0
Reserved				ADC10TB	ADC10CT	ADC10B1	ADC10FETCH
r0	r0	r0	r0	rw-(0)	rw-(0)	r-(0)	rw-(0)

Reserved	Bits 7-4	Reserved. Always read as 0.
ADC10TB	Bit 3	ADC10 two-block mode 0 One-block transfer mode 1 Two-block transfer mode
ADC10CT	Bit 2	ADC10 continuous transfer 0 Data transfer stops when one block (one-block mode) or two blocks (two-block mode) have completed. 1 Data is transferred continuously. DTC operation is stopped only if ADC10CT cleared, or ADC10SA is written to.
ADC10B1	Bit 1	ADC10 block one. This bit indicates for two-block mode which block is filled with ADC10 conversion results. ADC10B1 is valid only after ADC10IFG has been set the first time during DTC operation. ADC10TB must also be set. 0 Block 2 is filled 1 Block 1 is filled
ADC10FETCH	Bit 0	This bit should normally be reset.

ADC10DTC1 ADC10 Data Transfer Control Register 1

7	6	5	4	3	2	1	0
DTC Transfers							

7	6	5	4	3	2	1	0
DTC Transfers							
rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)	rw-(0)

DTC Transfers	Bits 7-0	DTC transfers. These bits define the number of transfers in each block. 0 DTC is disabled 01h-0FFh Number of transfers per block
----------------------	----------	--

ADC10SA Start Address Register for Data Transfer

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
ADC10SAx															0

ADC10SAx	Bits 15-1	ADC10 start address. These bits are the start address for the DTC. A write to register ADC10SA is required to initiate DTC transfers.
Unused	Bit 0	Unused, Read only. Always read as 0.